



Universal Mounting Kit

Proxim's 1000-UMK provides full axis alignment to Edge 1000 series and ORiNOCO AP-9200R.

Features and Specification

- Suitable for
 - Edge 1000 series
 - ORiNOCO AP-9200R
 - ORiNOCO AP-9100R
 - Tsunami 10000 compact series
 - Tsunami 800 series
- Pole Mounting
 - 1.5 to 3.25 inch
 - 38 to 82.5 mm
- Adjustment
 - Azimuth 360°
 - Elevation $\pm 30^\circ$
- Material
 - Stainless Steel 304

Package Contents

- One Universal Mounting Kit (1000-UMK)

Item	Description	Qty
A	Mounting Bracket	1
B	6 x 89 mm U-bolt	1
C	M6 Hex Nut	2
D	M6 Toothed Washer	2
E	M6 Flat Washer	6
F	1/4 inch Spring Washer	6
G	1/4 inch x 20 mm Pan Head Screw	4
	PE bag	1

Assemble the Mounting Hardware

- Place the L-Shaped Mounting Bracket onto the bottom of the device and align with the four mounting holes.
- Insert the Screw, Spring Washer and Flat Washer into the four mounting holes.
- Tighten the four screws to a torque of 100 lbf-in / 115 kgf-cm.
- The last image shows the fully assembled mounting hardware attached to the device.



Mount the Device

- Place the fully assembled mounting hardware along with the device against the pole and insert the U-bolt through the holes provided on full axis plate on the Mounting Bracket.
- Insert the Toothed Washer, Spring Washer, Flat Washer and Nut on both ends of the U-bolt
- Tighten the nut slightly so that the U-bolt is adjustable for pole mounting. After adjusting the angle of the device, fully tighten the nut.

